

Accessories













XP-6

Control Processor

The XP-6 is the powerful centerpiece of any professionally installed control system, designed to automate and enhance the operation of A/V, security, lighting, HVAC, and countless other devices in a commercial or residential environment. The XP-6 is packed with features to facilitate integration of third-party devices into one seamless and cohesive system, with a variety of communication options such as RS-232, relay, IP, and routable IR control. Additional RTI accessories can be incorporated to allow wireless communication between an RTI remote control and the XP-6, even through walls or cabinets. The processor features built-in support for the RTI 433-MHz receivers for one-way RF communication, or powerful ZigBee® 2.4-GHz transceivers can be incorporated for more sophisticated bidirectional communication between the RTI controller and central processor and supported devices.

Key Features

- Powerful 32bit, 533MHz CPU.
- 128Mb of non-volatile Flash memory.
- Six multi-purpose I/O ports.
- Three programmable 12VDC trigger outputs.
- Three assignable voltage sense inputs.
- · Three programmable relay outputs.
- Two RS-232 ports for bi-directional communication.
- Built-in astronomical clock for time-based events and sleep timers.
- Compatible with all RTI wireless remote controls (when used with RTI RF antennas/Zigbee® transceivers) and In-wall controllers.
- Multi-purpose I/O ports are compatible with industry standard IR emitters, blasters, and repeater systems.
- Input for connection of multiple RF receiver modules.
- Variable IR output on all ports.
- Multi-purpose I/O ports support all optional RTI power sensing and communications modules.
- Programmed using the Integration Designer® Software.
- Non-volatile Flash memory stores your system configuration even when power is not present.
- Fast USB 2.0 and Ethernet programming.
- Field upgradable firmware.



Specifications

Power Supply	.+12V DC, 1A
IR Output Ports	x 3.5mm jacks
	ard IR emitters
IR Output Drive	rt, adjustable)
200mA maximum (high I	R output port)
Infrared Frequency Transmission Range15	ikHz - 460kHz
Infrared Input	and receivers
Trigger OutputsThree, 12 VDC, 100	mA max each
RelaysThree, 5 Am	ps @ 30 VDC
Sense InputsTh	ree, 3-24VDC
RS-232 PortsTwo, Bi-directional RJ45	5 Connections
Ethernet Port	15 Connection
USB PortsOne,	Programming
RTI Com PortZigbee® Communication Port, RJ4	15 Connection
MountingWall-mount or	free standing
Operating Temperature+32°F to +122°F ('0°C to +50°C)
Operating Humidity5% to 95% Nor	n-Condensing
Dimensions (W x H x D) 10.3" (262mm) x 5.25" (134mm)	x 1.5" (38mm)
Weight	b. 3 oz. (543g)
Warranty Three Year (F	Parts & Labor)
All specifications subject to change without notice	



XP-6 Control Processor

RTI User Interfaces

RTiPanel	Mobile & PC Software Interface (App)
SURFIR	Companion Remote Control
T1-B+	Remote Control
T2i	Remote Control
T2x	Remote Control
T3x	Remote Control
RKM-1+	In-Wall Audio Distribution Keypad
RK1+	2-4-8 Button In-Wall Keypad
KX1	1.2" Audio Distribution Keypad
KX2	2.8" In-Wall Touchpanel Keypad
KX3	3.5" In-Wall Touchpanel Keypad
KX7	7" In-Wall Touchpanel
KX10	10" In-Wall Touchpanel
CX7	7" Countertop/Under-Cabinet Touchpanel
CX10	10" Countertop/Under-Cabinet Touchpanel

RTI Control Accessories

RP-4	RF Control Processor
XP-3	Advanced Control Processor
XP-6	Advanced Control Processor
XP-8v	Advanced Control Processor
RM433	433MHz RF Antenna
ZM24	2.4GHz Zigbee Transceiver
ZW-9	Z-Wave® Interface Module
CB-8	Touchpanel Connecting Block
CM-232	RS-232 Communication Module
CPB-1	Control Port Connecting Block
ECB-5	IR Connecting Block
ESC-2	Ethernet to Serial Converter
IPE-4	IR Port Expander
PCM-4	Port Control Module
RCM-4	Relay Control Module
IRsa Mouse	IR Emitter

RTI Audio/Video Distribution

AD-4x	4x4 Audio Distribution System
AD-8x	8x8 Audio Distribution System
AD-16x	16x16 Audio Distribution Matrix Switch
CP-450	4 Channel Cool Power® Amplifier
CP-1650	16 Channel Cool Power® Amplifier
VHD-4	4x4 HDBT Video Matrix Switch
VHD-8	8x8 HDBT Video Matrix Switch
VHT-1	HDBT Video Transmitter
VHR-1	HDBT Video Receiver



It's Under Control®